



Full credit is given to the above companies including the OS that this PDF file was generated!

Red Hat Enterprise Linux Release 9.2 Manual Pages on 'nvme-ana-log.1' command

\$ man nvme-ana-log.1

NVME-ANA-LOG(1) NVMe Manual NVME-ANA-LOG(1)

NAME

nvme-ana-log - Send NVMe ANA log page request, returns result and log

SYNOPSIS

nvme ana-log <device> [-o <fmt> | --output-format=<fmt>]

DESCRIPTION

Retrieves the NVMe Asymmetric Namespace Access log page from an NVMe device and provides the returned structure.

The <device> parameter is mandatory NVMe character device (ex: /dev/nvme0).

On success, the returned ANA log structure may be returned in one of several ways depending on the option flags; the structure may be parsed by the program and printed in a readable format or the raw buffer may be printed to stdout for another program to parse.

OPTIONS

-g, --groups

Return the list of ANA groups without the namespace listing.

-o <format>, --output-format=<format>

Set the reporting format to normal, json, or binary. Only one output format can be used at a time.

EXAMPLES

? Print the ANA log page in a human readable format:

```
# nvme ana-log /dev/nvme0
```

NVME

Part of the nvme-user suite

NVMe

06/23/2023

NVME-ANA-LOG(1)