



Full credit is given to the above companies including the OS that this PDF file was generated!

Rocky Enterprise Linux 9.2 Manual Pages on command 'sane-fujitsu.5'

\$ man sane-fujitsu.5

sane-fujitsu(5) SANE Scanner Access Now Easy sane-fujitsu(5)

NAME

sane-fujitsu - SANE backend for Fujitsu flatbed and ADF scanners

DESCRIPTION

The sane-fujitsu library implements a SANE (Scanner Access Now Easy) backend which provides access to most Fujitsu flatbed and ADF scanners.

This document describes backend version 136, which shipped with SANE 1.0.30.

SUPPORTED HARDWARE

This version supports every known model which speaks the Fujitsu SCSI and SCSI-over-USB protocols. Specifically, the SCSI M309x and M409x series, the SCSI fi-series, most of the USB fi-series, the USB ScanSnap S5xx/S15xx, and the USB iX1xx/5xx series scanners are supported. Please see the list at <http://www.sane-project.org/sane-supported-devices.html> for details.

This backend may support other Fujitsu scanners. The best way to determine level of support is to test the scanner directly, or to collect a trace of the windows driver in action. Please contact the author for

help or with test results.

UNSUPPORTED HARDWARE

The following scanners are known NOT to work with this backend, either because they have a non-fujitsu chipset, or an unsupported interface type. Some of these scanners may be supported by another backend.

```
-----  
SCSI:   SERIAL:  USB:  
-----  
  
ScanStation M3093E/DE/EX fi-4110EOX/2  
ScanPartner M3096EX    fi-4010CU  
SP-Jr      M3097E+/DE  S300/S300M  
SP-10/10C  M3099A/EH/EX S1300/S1100  
SP-15C/300C      fi-60F/65F  
SP-600C/620C     fi-5015C  
  
                SP-2x/3x
```

OPTIONS

Effort has been made to expose all hardware options, including:

source s

Selects the source for the scan. Options may include "Flatbed", "ADF Front", "ADF Back", "ADF Duplex", "Card Front", "Card Back", "Card Duplex".

mode m

Selects the mode for the scan. Options may include "Lineart", "Halftone", "Gray", and "Color".

resolution, y-resolution

Controls scan resolution. Setting --resolution also sets --y-resolution, though this behavior is overridden by some frontends.

tl-x, tl-y, br-x, br-y

Sets scan area upper left and lower right coordinates. These are renamed t, l, x, y by some frontends.

page-width, page-height

Sets paper size. Used by scanner to determine centering of scan

coordinates when using ADF and to detect double feed errors.

Other options will be available based on the capabilities of the scanner: machines with IPC or DTC will have additional enhancement options, those with CMP will have compression options, those with a printer will have a group of endorser options.

Additionally, several 'software' options are exposed by the backend. These are reimplementations of features provided natively by larger scanners, but running on the host computer. This enables smaller machines to have similar capabilities. Please note that these features are somewhat simplistic, and may not perform as well as the native implementations. Note also that these features all require that the driver cache the entire image in memory. This will almost certainly result in a reduction of scanning speed.

Use 'scanimage --help' to get a list, but be aware that some options may be settable only when another option has been set, and that advanced options may be hidden by some frontend programs.

CONFIGURATION FILE

The configuration file `fujitsu.conf` is used to tell the backend how to look for scanners, and provide options controlling the operation of the backend. This file is read each time the frontend asks the backend for a list of scanners, generally only when the frontend starts. If the configuration file is missing, the backend will be unable to locate any scanners.

Scanners can be specified in the configuration file in 4 ways:

"scsi FUJITSU"

Requests backend to search all scsi buses in the system for a device which reports itself to be a scanner made by 'FUJITSU'.

"scsi /dev/sg0" (or other scsi device file)

Requests backend to open the named scsi device. Only useful if you have multiple compatible scanners connected to your system, and need to specify one. Probably should not be used with the other "scsi" line above.

"usb 0x04c5 0x1042" (or other vendor/product ids)

Requests backend to search all usb buses in the system for a device which uses that vendor and product id. The device will then be queried to determine if it is a Fujitsu scanner.

"usb /dev/usb/scanner0" (or other device file)

Some systems use a kernel driver to access usb scanners. This method is untested.

The only configuration option supported is "buffer-size=xxx", allowing you to set the number of bytes in the data buffer to something other than the compiled-in default, 65536 (64K). Some users report that their scanner will "hang" mid-page, or fail to transmit the image if the buffer is not large enough.

Note: This option may appear multiple times in the configuration file.

It only applies to scanners discovered by 'scsi/usb' lines that follow this option.

Note: The backend does not place an upper bound on this value, as some users required it to be quite large. Values above the default are not recommended, and may crash your OS or lockup your scsi card driver. You have been warned.

ENVIRONMENT

The backend uses a single environment variable, SANE_DEBUG_FUJITSU, which enables debugging output to stderr. Valid values are:

5 Errors

10 Function trace

15 Function detail

20 Option commands

25 SCSI/USB trace

30 SCSI/USB writes

31 SCSI/USB reads

35 Useless noise

KNOWN ISSUES

Flatbed units may fail to scan at maximum area, particularly at high resolution.

Any model that does not support VPD during inquiry will not function

until an override is added to the backend.

CCITT Fax compression used by older scanners is not supported.

JPEG output is supported by the backend, but not by the SANE protocol,

so is disabled in this release. It can be enabled if you rebuild from

source.

CREDITS

m3091 backend: Frederik Ramm <frederik a t remote d o t org>

m3096g backend: Randolph Bentson <bentson a t holmsjoen d o t com>

(with credit to the unnamed author of the coolscan driver)

fujitsu backend, m3093, fi-4340C, ipc, cmp, long-time maintainer:

Oliver Schirrmeister <oschirr a t abm d o t de>

m3092: Mario Goppold <mgoppold a t tbzpariv d o t tcc-chemnitz dot de>

fi-4220C and basic USB support: Ron Cemer <ron a t roncemer d o t com>

fi-4120, fi-series color, backend re-write, jpeg, current maintainer:

m. allan noah: <kitno455 a t gmail d o t com>

JPEG output and low memory usage support funded by:

Archivista GmbH www.archivista.ch

Endorser support funded by:

O A S Oilfield Accounting Service Ltd

1500, 840 - 7th Avenue S.W.

Calgary, Alberta

T2P 3G2 Canada

1-403-263-2600 www.oas.ca

Automatic length detection support funded by:

Martin G. Miller [mgmiller at optonline.net](mailto:mgmiller@optonline.net)

Hardware donated, software image enhancement and fi-6/7xxx support

funded by:

Fujitsu Computer Products of America, Inc. www.fcpa.com

iX500 support funded by:

Prefix Computer Services www.prefixservice.com

SEE ALSO

sane(7), sane-scsi(5), sane-usb(5), sane-sp15c(5), sane-avision(5),

sane-epjitsu(5)

AUTHOR

m. allan noah: <kitno455 a t gmail d o t com>

07 Feb 2020

sane-fujitsu(5)