

**NAME**

TAPRIO – Time Aware Priority Shaper

**SYNOPSIS**

```
tc qdisc ... dev dev parent classid [ handle major: ] taprio num_tc tcs
    map P0 P1 P2 ... queues count1@offset1 count2@offset2 ...
    base-time base-time clockid clockid
    sched-entry <command 1> <gate mask 1> <interval 1>
    sched-entry <command 2> <gate mask 2> <interval 2>
    sched-entry <command 3> <gate mask 3> <interval 3>
    sched-entry <command N> <gate mask N> <interval N>
```

**DESCRIPTION**

The TAPRIO qdisc implements a simplified version of the scheduling state machine defined by IEEE 802.1Q-2018 Section 8.6.9, which allows configuration of a sequence of gate states, where each gate state allows outgoing traffic for a subset (potentially empty) of traffic classes.

How traffic is mapped to different hardware queues is similar to **mqprio(8)** and so the **map** and **queues** parameters have the same meaning.

The other parameters specify the schedule, and at what point in time it should start (it can behave as the schedule started in the past).

**PARAMETERS**

**num\_tc** Number of traffic classes to use. Up to 16 classes supported.

**map**

The priority to traffic class map. Maps priorities 0..15 to a specified traffic class. See **mqprio(8)** for more details.

**queues**

Provide count and offset of queue range for each traffic class. In the format, **count@offset**. Queue ranges for each traffic classes cannot overlap and must be a contiguous range of queues.

**base-time**

Specifies the instant in nanoseconds, using the reference of **clockid**, defining the time when the schedule starts. If 'base-time' is a time in the past, the schedule will start at

$\text{base-time} + (N * \text{cycle-time})$

where N is the smallest integer so the resulting time is greater than "now", and "cycle-time" is the sum of all the intervals of the entries in the schedule;

**clockid**

Specifies the clock to be used by qdisc's internal timer for measuring time and scheduling events.

**sched-entry**

There may multiple **sched-entry** parameters in a single schedule. Each one has the

**sched-entry** <command> <gatemask> <interval>

format. The only supported <command> is "S", which means "SetGateStates", following the IEEE

802.1Q-2018 definition (Table 8-7). <gate mask> is a bitmask where each bit is associated with a traffic class, so bit 0 (the least significant bit) being "on" means that traffic class 0 is "active" for that schedule entry. <interval> is a time duration, in nanoseconds, that specifies for how long that state defined by <command> and <gate mask> should be held before moving to the next entry.

#### flags

Specifies different modes for taprio. Currently, only txtime-assist is supported which can be enabled by setting it to 0x1. In this mode, taprio will set the transmit timestamp depending on the interval in which the packet needs to be transmitted. It will then utilize the **etf(8)** qdisc to sort and transmit the packets at the right time. The second example can be used as a reference to configure this mode.

#### txtime-delay

This parameter is specific to the txtime offload mode. It specifies the maximum time a packet might take to reach the network card from the taprio qdisc. The value should always be greater than the delta specified in the **etf(8)** qdisc.

## EXAMPLES

The following example shows how an traffic schedule with three traffic classes ("num\_tc 3"), which are separated different traffic classes, we are going to call these TC 0, TC 1 and TC 2. We could read the "map" parameter below as: traffic with priority 3 is classified as TC 0, priority 2 is classified as TC 1 and the rest is classified as TC 2.

The schedule will start at instant 1528743495910289987 using the reference CLOCK\_TAI. The schedule is composed of three entries each of 300us duration.

```
# tc qdisc replace dev eth0 parent root handle 100 taprio \
    num_tc 3 \
    map 2 2 1 0 2 2 2 2 2 2 2 2 2 2 2 2 \
    queues 1@0 1@1 2@2 \
    base-time 1528743495910289987 \
    sched-entry S 01 300000 \
    sched-entry S 02 300000 \
    sched-entry S 04 300000 \
    clockid CLOCK_TAI
```

Following is an example to enable the txtime offload mode in taprio. See **etf(8)** for more information about configuring the ETF qdisc.

```
# tc qdisc replace dev eth0 parent root handle 100 taprio \
    num_tc 3 \
    map 2 2 1 0 2 2 2 2 2 2 2 2 2 2 2 2 \
    queues 1@0 1@0 1@0 \
    base-time 1528743495910289987 \
    sched-entry S 01 300000 \
    sched-entry S 02 300000 \
    sched-entry S 04 400000 \
    flags 0x1 \
    txtime-delay 200000 \
    clockid CLOCK_TAI
```

```
# tc qdisc replace dev $IFACE parent 100:1 etf skip_skb_check \
    offload delta 200000 clockid CLOCK_TAI
```

**AUTHORS**

Vinicius Costa Gomes <vinicius.gomes@intel.com>